

## TABLA DE CONVERSION DE dB A ROE

---

PERDIDA DE RETORNO	ROE	PERDIDA POR REFLEXION	POTENCIA TRANSMITIDA	POTENCIA REFLEJADA
dB	1:	dB	%	%
1	17,3910	6,8683	20,57%	79,43%
2	8,7242	4,3292	36,90%	63,10%
3	5,8480	3,0206	49,88%	50,12%
4	4,4194	2,2048	60,19%	39,81%
5	3,5698	1,6509	68,38%	31,62%
6	3,0095	1,2563	74,88%	25,12%
7	2,6146	0,9665	80,05%	19,95%
8	2,3229	0,7494	84,15%	15,85%
9	2,0999	0,5844	87,41%	12,59%
10	1,9250	0,4576	90,00%	10,00%
11	1,7849	0,3594	92,06%	7,94%
12	1,6709	0,2830	93,69%	6,31%
13	1,5769	0,2233	94,99%	5,01%
14	1,4985	0,1764	96,02%	3,98%
15	1,4326	0,1396	96,84%	3,16%
16	1,3767	0,1105	97,49%	2,51%
17	1,3290	0,0875	98,00%	2,00%
18	1,2880	0,0694	98,42%	1,58%
19	1,2528	0,0550	98,74%	1,26%
20	1,2222	0,0436	99,00%	1,00%
21	1,1957	0,0346	99,21%	0,79%
22	1,1726	0,0275	99,37%	0,63%
23	1,1524	0,0218	99,50%	0,50%
24	1,1347	0,0173	99,60%	0,40%
25	1,1192	0,0138	99,68%	0,32%
26	1,1055	0,0109	99,75%	0,25%
27	1,0935	0,0087	99,80%	0,20%
28	1,0829	0,0069	99,84%	0,16%
29	1,0736	0,0055	99,87%	0,13%
30	1,0653	0,0043	99,90%	0,10%
31	1,0580	0,0035	99,92%	0,08%
32	1,0515	0,0027	99,94%	0,06%
33	1,0458	0,0022	99,95%	0,05%
34	1,0407	0,0017	99,96%	0,04%
35	1,0362	0,0014	99,97%	0,03%
36	1,0322	0,0011	99,97%	0,03%
37	1,0287	0,0009	99,98%	0,02%
38	1,0255	0,0007	99,98%	0,02%
39	1,0227	0,0005	99,99%	0,01%
40	1,0202	0,0004	99,99%	0,01%